

Xterm Control Sequences

Edward Moy

University of California, Berkeley

Revised by

Stephen Gildea

X Consortium

Definitions

- \boxed{c} The literal character c .
- C A single (required) character.
- P_s A single (usually optional) numeric parameter, composed of one or more digits.
- P_m A multiple numeric parameter composed of any number of single numeric parameters, separated by $\boxed{;}$ character(s).
- P_t A text parameter composed of printable characters.

VT100 Mode

Most of these control sequences are standard VT102 control sequences, but there are some sequences here from later DEC VT terminals, too. VT102 features not supported are smooth scrolling, double size characters, blinking characters, and VT52 mode. There are additional control sequences to provide *xterm*-dependent functions, like the scrollbar or window size. Where the function is specified by DEC or ISO 6429, the code assigned to it is given in parentheses. The escape codes to designate and invoke character sets are specified by ISO 2022; see that document for a discussion of character sets.

$\boxed{\text{BEL}}$	Bell (Ctrl-G)
$\boxed{\text{BS}}$	Backspace (Ctrl-H)
$\boxed{\text{TAB}}$	Horizontal Tab (HT) (Ctrl-I)
$\boxed{\text{LF}}$	Line Feed or New Line (NL) (Ctrl-J)
$\boxed{\text{VT}}$	Vertical Tab (Ctrl-K) same as LF
$\boxed{\text{FF}}$	Form Feed or New Page (NP) (Ctrl-L) same as LF
$\boxed{\text{CR}}$	Carriage Return (Ctrl-M)
$\boxed{\text{SO}}$	Shift Out (Ctrl-N) → Switch to Alternate Character Set: invokes the G1 character set.
$\boxed{\text{SI}}$	Shift In (Ctrl-O) → Switch to Standard Character Set: invokes the G0 character set (the default).
$\boxed{\text{ESC}} \boxed{\#} \boxed{8}$	DEC Screen Alignment Test (DECALN)
$\boxed{\text{ESC}} \boxed{(} \boxed{C}$	Designate G0 Character Set (ISO 2022)
	$C = \boxed{0}$ → DEC Special Character and Line Drawing Set
	$C = \boxed{A}$ → United Kingdom (UK)

<code>ESC</code> <code>[</code> <code>B</code> <code>C</code>	$C = \overline{B}$ → United States (USASCII) Designate G1 Character Set (ISO 2022) $C = \overline{0}$ → DEC Special Character and Line Drawing Set $C = \overline{A}$ → United Kingdom (UK) $C = \overline{B}$ → United States (USASCII)
<code>ESC</code> <code>[</code> <code>*</code> <code>C</code>	Designate G2 Character Set (ISO 2022) $C = \overline{0}$ → DEC Special Character and Line Drawing Set $C = \overline{A}$ → United Kingdom (UK) $C = \overline{B}$ → United States (USASCII)
<code>ESC</code> <code>[</code> <code>+</code> <code>C</code>	Designate G3 Character Set (ISO 2022) $C = \overline{0}$ → DEC Special Character and Line Drawing Set $C = \overline{A}$ → United Kingdom (UK) $C = \overline{B}$ → United States (USASCII)
<code>ESC</code> <code>[</code> <code>7</code>	Save Cursor (DECSA)
<code>ESC</code> <code>[</code> <code>8</code>	Restore Cursor (DECRB)
<code>ESC</code> <code>[</code> <code>=</code>	Application Keypad (DECPAM)
<code>ESC</code> <code>[</code> <code>></code>	Normal Keypad (DECPNM)
<code>ESC</code> <code>[</code> <code>D</code>	Index (IND)
<code>ESC</code> <code>[</code> <code>E</code>	Next Line (NEL)
<code>ESC</code> <code>[</code> <code>F</code>	Cursor to lower left corner of screen (if enabled by the hpLowerleftBugCompat resource).
<code>ESC</code> <code>[</code> <code>H</code>	Tab Set (HTS)
<code>ESC</code> <code>[</code> <code>M</code>	Reverse Index (RI)
<code>ESC</code> <code>[</code> <code>N</code>	Single Shift Select of G2 Character Set (SS2): affects next character only
<code>ESC</code> <code>[</code> <code>O</code>	Single Shift Select of G3 Character Set (SS3): affects next character only
<code>ESC</code> <code>[</code> <code>P</code> P_t <code>ESC</code> <code>[</code> <code>\</code>	Device Control String (DCS) <i>xterm</i> implements no DCS functions; P_t is ignored. P_t need not be printable characters.
<code>ESC</code> <code>[</code> <code>Z</code>	Return Terminal ID (DECID). Obsolete form of <code>ESC</code> <code>[</code> <code>[</code> <code>c</code> (DA).
<code>ESC</code> <code>[</code> <code>[</code> P_s <code>@</code>	Insert P_s (Blank) Character(s) (default = 1) (ICH)
<code>ESC</code> <code>[</code> <code>[</code> P_s <code>A</code>	Cursor Up P_s Times (default = 1) (CUU)
<code>ESC</code> <code>[</code> <code>[</code> P_s <code>B</code>	Cursor Down P_s Times (default = 1) (CUD)
<code>ESC</code> <code>[</code> <code>[</code> P_s <code>C</code>	Cursor Forward P_s Times (default = 1) (CUF)
<code>ESC</code> <code>[</code> <code>[</code> P_s <code>D</code>	Cursor Backward P_s Times (default = 1) (CUB)
<code>ESC</code> <code>[</code> <code>[</code> P_s <code>;</code> P_s <code>H</code>	Cursor Position [row;column] (default = [1,1]) (CUP)
<code>ESC</code> <code>[</code> <code>[</code> P_s <code>J</code>	Erase in Display (ED) $P_s = \overline{0}$ → Clear Below (default) $P_s = \overline{1}$ → Clear Above $P_s = \overline{2}$ → Clear All
<code>ESC</code> <code>[</code> <code>[</code> P_s <code>K</code>	Erase in Line (EL) $P_s = \overline{0}$ → Clear to Right (default) $P_s = \overline{1}$ → Clear to Left

	$P_s = \boxed{2}$	→ Clear All
$\overline{\text{ESC}} \boxed{} \boxed{} P_s \boxed{\text{L}}$		Insert P_s Line(s) (default = 1) (IL)
$\overline{\text{ESC}} \boxed{} \boxed{} P_s \boxed{\text{M}}$		Delete P_s Line(s) (default = 1) (DL)
$\overline{\text{ESC}} \boxed{} \boxed{} P_s \boxed{\text{P}}$		Delete P_s Character(s) (default = 1) (DCH)
$\overline{\text{ESC}} \boxed{} \boxed{} P_s \boxed{;}; P_s \boxed{;}; P_s \boxed{;}; P_s \boxed{;}; P_s \boxed{\text{T}}$		Initiate hilite mouse tracking. Parameters are [func;startx;starty;firstrow;lastrow]. See the section Mouse Tracking .
$\overline{\text{ESC}} \boxed{} \boxed{} P_s \boxed{\text{c}}$		Send Device Attributes (DA)
	$P_s = \boxed{0}$ or omitted	→ request attributes from terminal
	→ $\overline{\text{ESC}} \boxed{} \boxed{} ? \boxed{1} \boxed{;}; \boxed{2} \boxed{\text{c}}$	(“I am a VT100 with Advanced Video Option.”)
$\overline{\text{ESC}} \boxed{} \boxed{} P_s \boxed{;}; P_s \boxed{\text{f}}$		Horizontal and Vertical Position [row;column] (default = [1,1]) (HVP)
$\overline{\text{ESC}} \boxed{} \boxed{} P_s \boxed{\text{g}}$		Tab Clear (TBC)
	$P_s = \boxed{0}$	→ Clear Current Column (default)
	$P_s = \boxed{3}$	→ Clear All
$\overline{\text{ESC}} \boxed{} \boxed{} P_m \boxed{\text{h}}$		Set Mode (SM)
	$P_s = \boxed{4}$	→ Insert Mode (IRM)
	$P_s = \boxed{2} \boxed{0}$	→ Automatic Newline (LNM)
$\overline{\text{ESC}} \boxed{} \boxed{} P_m \boxed{\text{l}}$		Reset Mode (RM)
	$P_s = \boxed{4}$	→ Replace Mode (IRM)
	$P_s = \boxed{2} \boxed{0}$	→ Normal Linefeed (LNM)
$\overline{\text{ESC}} \boxed{} \boxed{} P_m \boxed{\text{m}}$		Character Attributes (SGR)
	$P_s = \boxed{0}$	→ Normal (default)
	$P_s = \boxed{1}$	→ Bold
	$P_s = \boxed{4}$	→ Underscore
	$P_s = \boxed{5}$	→ Blink (appears as Bold)
	$P_s = \boxed{7}$	→ Inverse
$\overline{\text{ESC}} \boxed{} \boxed{} P_s \boxed{\text{n}}$		Device Status Report (DSR)
	$P_s = \boxed{5}$	→ Status Report $\overline{\text{ESC}} \boxed{} \boxed{} \boxed{0} \boxed{\text{n}}$ (“OK”)
	$P_s = \boxed{6}$	→ Report Cursor Position (CPR) [row;column] as $\overline{\text{ESC}} \boxed{} \boxed{} r \boxed{;}; c \boxed{\text{R}}$
$\overline{\text{ESC}} \boxed{} \boxed{} P_s \boxed{;}; P_s \boxed{\text{r}}$		Set Scrolling Region [top;bottom] (default = full size of window) (DECSTBM)
$\overline{\text{ESC}} \boxed{} \boxed{} P_s \boxed{\text{x}}$		Request Terminal Parameters (DECREQTPARM)
$\overline{\text{ESC}} \boxed{} \boxed{} ? \boxed{P_m} \boxed{\text{h}}$		DEC Private Mode Set (DECSET)
	$P_s = \boxed{1}$	→ Application Cursor Keys (DECCKM)
	$P_s = \boxed{2}$	→ Designate USASCII for character sets G0-G3. (In the VT102, this selects VT52 mode (DECANM), which <i>xterm</i> doesn't support.)
	$P_s = \boxed{3}$	→ 132 Column Mode (DECCOLM)
	$P_s = \boxed{4}$	→ Smooth (Slow) Scroll (DECSCLM)
	$P_s = \boxed{5}$	→ Reverse Video (DECSCNM)
	$P_s = \boxed{6}$	→ Origin Mode (DECOM)
	$P_s = \boxed{7}$	→ Wraparound Mode (DECAWM)
	$P_s = \boxed{8}$	→ Auto-repeat Keys (DECARM)

$P_s = \overline{9}$ → Send Mouse X & Y on button press. See the section **Mouse Tracking**.

$P_s = \overline{3} \overline{8}$ → Enter Tektronix Mode (DECTEK)

$P_s = \overline{4} \overline{0}$ → Allow 80 ↔ 132 Mode

$P_s = \overline{4} \overline{1}$ → *more*(1) fix (see *curses* resource)

$P_s = \overline{4} \overline{4}$ → Turn On Margin Bell

$P_s = \overline{4} \overline{5}$ → Reverse-wraparound Mode

$P_s = \overline{4} \overline{6}$ → Start Logging (normally disabled by a compile-time option)

$P_s = \overline{4} \overline{7}$ → Use Alternate Screen Buffer (unless disabled by the **titeInhibit** resource)

$P_s = \overline{1} \overline{0} \overline{0} \overline{0}$ → Send Mouse X & Y on button press and release. See the section **Mouse Tracking**.

$P_s = \overline{1} \overline{0} \overline{0} \overline{1}$ → Use Hilite Mouse Tracking. See the section **Mouse Tracking**.

$\overline{\text{ESC}} \overline{[} \overline{?} P_m \overline{1}$

DEC Private Mode Reset (DECRST)

$P_s = \overline{1}$ → Normal Cursor Keys (DECCKM)

$P_s = \overline{3}$ → 80 Column Mode (DECCOLM)

$P_s = \overline{4}$ → Jump (Fast) Scroll (DECSCLM)

$P_s = \overline{5}$ → Normal Video (DECSCNM)

$P_s = \overline{6}$ → Normal Cursor Mode (DECOM)

$P_s = \overline{7}$ → No Wraparound Mode (DECAWM)

$P_s = \overline{8}$ → No Auto-repeat Keys (DECARM)

$P_s = \overline{9}$ → Don't Send Mouse X & Y on button press

$P_s = \overline{4} \overline{0}$ → Disallow 80 ↔ 132 Mode

$P_s = \overline{4} \overline{1}$ → No *more*(1) fix (see *curses* resource)

$P_s = \overline{4} \overline{4}$ → Turn Off Margin Bell

$P_s = \overline{4} \overline{5}$ → No Reverse-wraparound Mode

$P_s = \overline{4} \overline{6}$ → Stop Logging (normally disabled by a compile-time option)

$P_s = \overline{4} \overline{7}$ → Use Normal Screen Buffer

$P_s = \overline{1} \overline{0} \overline{0} \overline{0}$ → Don't Send Mouse X & Y on button press and release

$P_s = \overline{1} \overline{0} \overline{0} \overline{1}$ → Don't Use Hilite Mouse Tracking

$\overline{\text{ESC}} \overline{[} \overline{?} P_m \overline{r}$

Restore DEC Private Mode Values. The value of P_s previously saved is restored. P_s values are the same as for DECSET.

$\overline{\text{ESC}} \overline{[} \overline{?} P_m \overline{s}$

Save DEC Private Mode Values. P_s values are the same as for DECSET.

$\overline{\text{ESC}} \overline{[} P_s \overline{;} P_t \overline{\text{BEL}}$

Set Text Parameters

$P_s = \overline{0}$ → Change Icon Name and Window Title to P_t

$P_s = \overline{1}$ → Change Icon Name to P_t

$P_s = \overline{2}$ → Change Window Title to P_t

$P_s = \overline{4} \overline{6}$ → Change Log File to P_t (normally disabled by a compile-time option)

$P_s = \overline{5} \overline{0}$ → Set Font to P_t

$\overline{\text{ESC}} \overline{\text{^}} P_t \overline{\text{ESC}} \overline{\backslash}$

Privacy Message (PM)

xterm implements no PM functions; P_t is ignored. P_t need not be printable characters.

<code>ESC</code> <code>[</code> <code>P</code> <code>i</code> <code>ESC</code> <code>\</code> <code>\</code>	Application Program Command (APC) <i>xterm</i> implements no APC functions; P_i is ignored. P_i need not be printable characters.
<code>ESC</code> <code>c</code>	Full Reset (RIS)
<code>ESC</code> <code>[</code> <code>I</code>	Memory Lock (per HP terminals). Locks memory above the cursor.
<code>ESC</code> <code>[</code> <code>m</code>	Memory Unlock (per HP terminals)
<code>ESC</code> <code>[</code> <code>n</code>	Invoke the G2 Character Set (LS2)
<code>ESC</code> <code>[</code> <code>o</code>	Invoke the G3 Character Set (LS3)
<code>ESC</code> <code>[</code> <code> </code>	Invoke the G3 Character Set as GR (LS3R). Has no visible effect in <i>xterm</i> .
<code>ESC</code> <code>[</code> <code>}</code>	Invoke the G2 Character Set as GR (LS2R). Has no visible effect in <i>xterm</i> .
<code>ESC</code> <code>[</code> <code>~</code>	Invoke the G1 Character Set as GR (LS1R). Has no visible effect in <i>xterm</i> .

Mouse Tracking

The VT widget can be set to send the mouse position and other information on button presses. These modes are typically used by editors and other full-screen applications that want to make use of the mouse.

There are three mutually exclusive modes, each enabled (or disabled) by a different parameter in the DECSET (or DECRST) escape sequence. Parameters for all mouse tracking escape sequences generated by *xterm* encode numeric parameters in a single character as *value*+040. For example, `[!]` is 1. The screen coordinate system is 1-based.

X10 compatibility mode sends an escape sequence on button press encoding the location and the mouse button pressed. It is enabled by specifying parameter 9 to DECSET. On button press, *xterm* sends `ESC [[M Cb Cx Cy` (6 characters). C_b is button-1. C_x and C_y are the x and y coordinates of the mouse when the button was pressed.

Normal tracking mode sends an escape sequence on both button press and release. Modifier information is also sent. It is enabled by specifying parameter 1000 to DECSET. On button press or release, *xterm* sends `ESC [[M Cb Cx Cy`. The low two bits of C_b encode button information: 0=MB1 pressed, 1=MB2 pressed, 2=MB3 pressed, 3=release. The upper bits encode what modifiers were down when the button was pressed and are added together. 4=Shift, 8=Meta, 16=Control. C_x and C_y are the x and y coordinates of the mouse event. The upper left corner is (1,1).

Mouse hilite tracking notifies a program of a button press, receives a range of lines from the program, highlights the region covered by the mouse within that range until button release, and then sends the program the release coordinates. It is enabled by specifying parameter 1001 to DECSET. Warning: use of this mode requires a cooperating program or it will hang *xterm*. On button press, the same information as for normal tracking is generated; *xterm* then waits for the program to send mouse tracking information. *All X events are ignored until the proper escape sequence is received from the pty:* `ESC [[Ps ; Ps ; Ps ; Ps ; Ps T`. The parameters are *func*, *startx*, *starty*, *firstrow*, and *lastrow*. *func* is non-zero to initiate hilite tracking and zero to abort. *startx* and *starty* give the starting x and y location for the highlighted region. The ending location tracks the mouse, but will never be above row *firstrow* and will always be above row *lastrow*. (The top of the screen is row 1.) When the button is released, *xterm* reports the ending position one of two ways: if the start and end coordinates are valid text locations: `ESC [[t Cx Cy`. If either coordinate is past the end of the line: `ESC [[T Cx Cy Cx Cy`. The parameters are *startx*, *starty*, *endx*, *endy*, *mousex*, and *mousey*. *startx*, *starty*, *endx*, and *endy* give the starting and ending character positions of the region. *mousex* and *mousey* give the location of the mouse at button up, which may not be over a character.

Tektronix 4014 Mode

Most of these sequences are standard Tektronix 4014 control sequences. Graph mode supports the 12-bit addressing of the Tektronix 4014. The major features missing are the write-thru and defocused modes. This document does not describe the commands used in the various Tektronix plotting modes but does describe the commands to switch modes.

<code>BEL</code>	Bell (Ctrl-G)
<code>BS</code>	Backspace (Ctrl-H)
<code>TAB</code>	Horizontal Tab (Ctrl-I)
<code>LF</code>	Line Feed or New Line (Ctrl-J)
<code>VT</code>	Cursor up (Ctrl-K)
<code>FF</code>	Form Feed or New Page (Ctrl-L)
<code>CR</code>	Carriage Return (Ctrl-M)
<code>ESC</code> <code>ETX</code>	Switch to VT100 Mode (ESC Ctrl-C)
<code>ESC</code> <code>ENQ</code>	Return Terminal Status (ESC Ctrl-E)
<code>ESC</code> <code>FF</code>	PAGE (Clear Screen) (ESC Ctrl-L)
<code>ESC</code> <code>SO</code>	Begin 4015 APL mode (ignored by <i>xterm</i>) (ESC Ctrl-N)
<code>ESC</code> <code>SI</code>	End 4015 APL mode (ignored by <i>xterm</i>) (ESC Ctrl-O)
<code>ESC</code> <code>ETB</code>	COPY (Save Tektronix Codes to file COPYyy-mm-dd.hh:mm:ss) (ESC Ctrl-W)
<code>ESC</code> <code>CAN</code>	Bypass Condition (ESC Ctrl-X)
<code>ESC</code> <code>SUB</code>	GIN mode (ESC Ctrl-Z)
<code>ESC</code> <code>FS</code>	Special Point Plot Mode (ESC Ctrl-\)
<code>ESC</code> <code>8</code>	Select Large Character Set
<code>ESC</code> <code>9</code>	Select #2 Character Set
<code>ESC</code> <code>:</code>	Select #3 Character Set
<code>ESC</code> <code>;</code>	Select Small Character Set
<code>ESC</code> <code>] P_s ; P_t BEL</code>	Set Text Parameters of VT window
	$P_s = \underline{0}$ → Change Icon Name and Window Title to P_t
	$P_s = \underline{1}$ → Change Icon Name to P_t
	$P_s = \underline{2}$ → Change Window Title to P_t
	$P_s = \underline{4} \underline{6}$ → Change Log File to P_t (normally disabled by a compile-time option)
<code>ESC</code> <code>`</code>	Normal Z Axis and Normal (solid) Vectors
<code>ESC</code> <code>a</code>	Normal Z Axis and Dotted Line Vectors
<code>ESC</code> <code>b</code>	Normal Z Axis and Dot-Dashed Vectors
<code>ESC</code> <code>c</code>	Normal Z Axis and Short-Dashed Vectors
<code>ESC</code> <code>d</code>	Normal Z Axis and Long-Dashed Vectors
<code>ESC</code> <code>h</code>	Defocused Z Axis and Normal (solid) Vectors
<code>ESC</code> <code>i</code>	Defocused Z Axis and Dotted Line Vectors
<code>ESC</code> <code>j</code>	Defocused Z Axis and Dot-Dashed Vectors
<code>ESC</code> <code>k</code>	Defocused Z Axis and Short-Dashed Vectors
<code>ESC</code> <code>l</code>	Defocused Z Axis and Long-Dashed Vectors
<code>ESC</code> <code>p</code>	Write-Thru Mode and Normal (solid) Vectors
<code>ESC</code> <code>q</code>	Write-Thru Mode and Dotted Line Vectors
<code>ESC</code> <code>r</code>	Write-Thru Mode and Dot-Dashed Vectors
<code>ESC</code> <code>s</code>	Write-Thru Mode and Short-Dashed Vectors
<code>ESC</code> <code>t</code>	Write-Thru Mode and Long-Dashed Vectors

FS

Point Plot Mode (Ctrl-\)

GS

Graph Mode (Ctrl-])

RS

Incremental Plot Mode (Ctrl-^)

US

Alpha Mode (Ctrl-_)